

SETTING UP SCAN TO NETWORK FOLDER ON OKI ES8460/ES8462

1 - OBTAIN THE IP ADDRESS OF YOUR COPIER

ON THE COPIER


PRESS THE SETUP BUTTON

THEN VIEW INFORMATION

THEN NETWORK

NOTE THE IPV4 ADDRESS


2 - OPEN UP YOUR WEB BROWSER (MUST BE FROM A PC THAT IS CONNECTED TO THE SAME NETWORK) AND TYPE THE IP ADDRESS INTO THE ADDRESS BAR



The image shows a screenshot of a web browser window. The address bar at the top contains the IP address "192.168.1.8". Below the address bar, the Google logo is displayed in its characteristic multi-colored font. A search input field is visible below the logo, and two buttons labeled "Google Search" and "I'm Feeling Lucky" are positioned below the search field. An arrow points from the text "TYPE ADDRESS IN HERE" to the address bar. The browser's menu bar and toolbar are also visible at the top of the window.

TYPE ADDRESS IN HERE


3 - YOU WILL NOW SEE THE FOLLOWING SCREEN



4 - CLICK ON THE ADMINISTRATOR LOGIN

5 - ENTER THE USERNAME AND PASSWORD (default settings are username: admin password: aaaaa) AND CLICK OK

6 - IF THIS SCREEN APPEARS SCROLL DOWN AND CLICK SKIP OTHERWISE PROCEED TO NEXT STEP



7 - CLICK ON PROFILE

OKI
PRINTING SOLUTIONS

ES8462 MFP Refresh Status Window

[View Info](#) | [Reports](#) | [Paper Setup](#) | [Profile](#) | [Admin Setup](#) | [Job List](#) | [Direct Print](#) | [Transmission Settings](#) | [Links](#)

View Information

- Status
- Counter
- Supplies Life
- Usage Report
- Network
- System

Alert Information

WARNING Paper Out Warning

Information

Device Name	OKI-ES8462MFP-8E89F6
IP Address	192.168.1.8
MAC Address	00:25:36:8E:89:F6
Location	
Serial Number	AL52017580
Asset Number	
Contact Name - Administrator	
Tray1	A4 SEF
Tray2	A4 SEF
Tray3	A4 SEF
MP Tray	A4 LEF
Duplex	Installed
Hard Disk	Installed
Memory	512 MB

Version Information

CU	05.15
PU	00.07.02
Network Firmware	05.02
Web Remote	05.00
Web Language	05.00

Toner Remain :

Black: 30%
 Cyan: 30%
 Magenta: 50%
 Yellow: 40%

Print Service Enabled

LPR	<input checked="" type="radio"/>
Port9100	<input checked="" type="radio"/>
FTP	<input type="radio"/>
IPP	<input type="radio"/>
NetWare PServer	<input checked="" type="radio"/>
NetWare RPrinter	<input type="radio"/>
EtherTalk	<input checked="" type="radio"/>
NetBEUI	<input type="radio"/>

Setting Service Enabled

SNMP	<input checked="" type="radio"/>
WEB	<input checked="" type="radio"/>
Telnet	<input type="radio"/>
NetBEUI	<input type="radio"/>

Copyright (c) 2012 Oki Data Corporation. All rights reserved.

8 - THE FOLLOWING BOX WILL NOW APPEAR - CLICK ON NEW

OKI
PRINTING SOLUTIONS

ES8462 MFP

[View Info](#) | [Reports](#) | [Paper Setup](#) | [Profile](#) | [Admin Setup](#) | [Job List](#) | [Direct Print](#) | [Transmission Settings](#) | [Links](#)

Profile

Profile

Profile

New Delete Edit

Profile List:

Profile Counter 0 / 50

ES8462 MFP - Internet Explorer
 http://192.168.1.8/profileadd.htm

Profile Settings

Profile Name	<input type="text"/> (Max.16 characters)
Protocol	CIFS
Target URL	<input type="text"/> (Max.144 characters) Example: \\TESTCOMPUTER\TEST
Port No.	445 (1-65535)
User Name	<input type="text"/> (Max.32 characters)
Password	<input type="password"/> (Max.32 characters)
CIFS character set	UTF-16
Encode Communication	None
File Name	<input type="text"/> (Max.64 characters) Example: Image#n. The sequential number is given to the place of "#n". Image#d. Date is given to the place of "#d".
Doc. Type	Text&Photo
Back and Show-Thru Removal	AUTO
Density	0
Resolution	200 dpi
Scan Size	AUTO
Contrast	0
Hue	0
Saturation	0
Grayscale	OFF

9 - ENTER A PROFILE NAME ie. Scan to Desktop

10 - ENTER THE DESTINATION IN THE FOLLOWING FORMAT

\\'FRONTDESK'\SCANS'

'FRONTDESK' = COMPUTER NAME

'SCANS' = SHARE NAME

11 - ENTER A USERNAME AND PASSWORD (if none is required use Guest as the username and leave password blank)

12 - ENTER A DEFAULT FILE NAME FORMAT IF UNSURE USE

DOCUMENT#N

13 - SCROLL DOWN AND CLICK SUBMIT